

FERMAX

Duox Plus 7" Iris Smart Wi-Fi monitor

Available in **black or white.**



ref.9265

Dimensions:
190 x 155 x 19 mm.

7" responsive touch screen (16:9) with OSD menu.
Resolution: 1024 x 600 px.

Status icon LEDs with white light: power, Wi-Fi, missed calls, doormatic, do not disturb.

Digital microphone and speaker.

Quick access bar.

Date and time.

Made of **high-impact ABS plastic.**



Auto-on function. Activates the entrance panel camera without a prior call and changes visualisation to another entrance panel or camera.

"Do not disturb" function.

Flat mechanical pushbuttons.

ref.9264



Duox Plus technology: the only 100% digital Smart System in 2 wires.



Capacitive touch screen with a customisable interface: icons can be added, removed or rearranged.



Audio system with a digital microphone and speaker.



Manual or automatic image and video capture from the monitor or mobile.



Intercom function. Enables simple and direct communication between monitors installed within the same home (up to 3).



User experience. Choice of melodies (up to 7 options). Timed "do not disturb" function. Configurable F1 and F2 function buttons to activate a second entrance, courtesy lighting and more (Duox Plus relay required). Adjustable call and conversation volume. Integrated apartment entrance doorbell, with no additional devices required.



Real-time web browsing to access live information (weather, traffic, etc.) or connect to home automation servers.



Wi-Fi as standard. Connectivity is integrated directly into the monitor, including the free and unlimited DuoxMe call divert to mobile service.



IP camera visualisation.
Up to 4 IP cameras with RTSP streaming.
Digital video peephole function.



Doormatic function. Allows the door to be programmed to open automatically whenever a call is received.



Technical specifications

Installation	Surface*
Power supply	18-24 Vcc
Maximum consumption	12 W
Working temperature	from -10 to +55 °C
Connectivity	Wi-Fi (2.4GHz)

*With white connector (ref. 9447) or black connector (ref. 9457).



MORE INFO

CALL DIVERT TO MOBILE



DuoxMe
FERMAX

Free and unlimited APP

- Answer calls from the video intercom on your mobile.
- Check the images of those who called. Download and share them.
- Activate the camera to see what's happening outside your home.

- Open without keys.
- Open the door from Widget (Android) and Shortcuts (iOS)
- Open the door with Alexa, Google Home, Siri or Apple Watch.
- Invite family and friends. 1 master + 5 guest users. 2 devices per user.